

Showing the IP BOLD's video on a Snom IP phone

Your Snom IP phone can show the video of your IP BOLD video doorbell intercom.

Prerequisites:

- Snom phone Firmware greater than 8.7.3.19
- Snom phone must have a graphic display (currently 760, 765, 821 and 870)
- IP BOLD door entry station must be an extension of the same PBX where the Snom phone is registered

How to:

- Access the web user interface of your Snom phone.
- Select "directory"
- Create a new entry as follows:



The screenshot shows the Snom web interface. On the left is a navigation menu with sections: Operation (Home, Directory), Setup (Preferences, Speed Dial, Function Keys, Identity 1-12, Action URL Settings, Advanced, Certificates, Software Update), and Status (System Information). The main content area is titled 'Directory' and contains a table with columns: Name, Number, Contact Type, Outgoing Identity, Edit, and Delete. Below the table is the 'Add or Edit Entry' form. The 'Number' field is set to '51'. The 'Action-Url' field contains 'http://172.16.1.201/snom01.xml'. The 'Nickname' field is set to 'Doorbell'. A callout box with an arrow points to the 'Action-Url' field, stating 'IP address of IP BOLD'.

„To display video of the Snom IP video phone without making the call: Go to Snom setup, page 'Function keys', enter 'Type'='Action URL', 'Number'='http://192.168.1.250/snom01.xml' or any of your current http address, of course.“

When a call from extension 51 (as in this example) arrives, then the content of the field “Action-Url” will be executed, which will show the current video of the IP Bold doorstation.

It is also possible to add the same URL in one of the fields of function key, so you can open up the video of IP Bold without having received a call:

Context	Type	Number	Short Text	
Active	Action URL	http://172.16.1.201/snom01	Doorbell	P1
Active	Line			P2