

Loxone smart home system – IP VarioBell sip video intercom

quick setup of video and audio path

<https://www.loxone.com/en/en/>
<http://www.alphatechtechnologies.cz/en/products/voip-door-phones/ip-door-entry-phone-station-ip-variobell/>

- 1) Make a SIP server registration, Create your own SIP extension, for example:

Free SIP service

[Logout](#)
[Change your password](#)
[Delete your account](#)

Welcome neumann p : update your account

Firstname

Name

Do you want to keep in touch with linphone updates ?
 Keep me informed No thanks

Your SIP information

Sip identity : t██████████@sip.linphone.org
Username : t██████████
Email : ██████████@██████████.cz
Domain / Proxy : sip.linphone.org

<https://www.linphone.org/free-sip-service.html>



- 2) IP VarioBell – sip registration to a SIP server, register your SIP extension, for example:

Nastavení SIP

Režim:	SIP server <input type="button" value="v"/>
Název - jmenovka:	SIPbranka
SIP User Agent:	t [redacted]
Jméno:	t [redacted]
Auth. Id:	t [redacted]
Heslo:
Posílat registraci:	<input checked="" type="checkbox"/>
Registrační server:	sip.linphone.org
Port:	5060
Platnost [sec]:	600
Odregistrovat při restartu:	<input checked="" type="checkbox"/>
SIP proxy server:	sip.linphone.org
Port:	5060
Outbound proxy:	
Port:	5060
SIP Transport:	TCP & UDP <input type="button" value="v"/>
Provisional code:	Použít 180 (Ringing) <input type="button" value="v"/>
Použít Symetrické RTP:	<input type="checkbox"/>

Registrace úspěšná

- 3) Fill out video and audio path in the Loxone smart home system, for example

Obraz po zazvonění	
URL Videostream (interní)	http://192.168.1.250:1234/v...
URL Videostream (externí)	[redacted].../v...
Uživatelské jméno kamery	
Heslo pro kameru	Uzivatelскеjmeno:heslo
Host pro Audio	192.168.1.250
Host pro Audio (externí)	sip.linphone.org
Uživatelské jméno	t [redacted]
Uživatelské jméno pro Audio...	t [redacted]

Video mjpg path for the camera of the IP VarioBell intercom:
 ip_address_of_the_intercom/video.mjpg

SIP communication (audio) of IP VarioBell intercom:
http://name:password@ip_address_of_the_intercom_or_...@sip.linphone.org

